


Series 1 - T-61A cavity buna-N cartridge seal kit

Model: **990-061-007**



Technical Features

• The shelf life for a Buna-N cartridge seal kit is ten years from date of purchase. This date will be printed on the kit packaging.

Cartridge Installation Data

| tar arage instantation bata | | | | |
|-----------------------------|----------------|---------------------|--|--|
| | U.S. Units | Metric Units | | |
| Cavity | T-6 | T-61A | | |
| Cartridge Thread | M2 | M20 | | |
| Valve Hex Size | 7/8 in. | 22,2 mm | | |
| Valve Installation Torque | 30 - 35 lbf ft | 40 - 50 Nm | | |

990-061-007

What models can this kit be used on?

DCCA DCCB DCCC DCCD DCCF XRCC

Display Components

| | Description | Quantity | View |
|-------------|-------------|----------|------|
| 500-002-017 | O-Ring | 2 | B,C |
| 515-002-016 | Backup Ring | 1 | С |
| 515-002-015 | Backup Ring | 2 | D |
| 515-002-017 | Backup Ring | 2 | В |
| 500-001-018 | O-Ring | 1 | Α |
| 515-002-018 | Backup Ring | 1 | Α |
| 500-001-014 | O-Ring | 2 | E |
| 500-001-015 | O-Ring | 1 | D |
| 515-002-014 | Backup Ring | 4 | Е |
| 999-019-101 | Literature | 1 | |
| | | | |

Instructions/Notes

- Install back-up rings and O-rings as shown in views.
- When installing continuous back-up rings, use the same technique and the same care used to install O-rings.
- When installing cartridge be sure to torque to recommended value.